

**Features:**

1. AC input range selectable by switch
2. Protections: Short circuit/Over load/Over voltage
3. Forced air cooling by built-in DC ball bearing fan

MODEL		S-200-12
OUTPUT	DC VOLTAGE	12V
	RATED CURRENT	16.5A
	CURRENT RANGE	0 ~ 16.5A
	RATED POWER	200W
	RIPPLE & NOISE (max.)	180mVp-p
	VOLTAGE ADJ. RANGE	10.6 ~ 13.2V
	VOLTAGE TOLERANCE	±1.0%
	LINE REGULATION	±0.5%
	LOAD REGULATION	±0.5%
SETUP, RISE, HOLD TIME	200ms, 80ms, 16ms at full load	
INPUT	VOLTAGE RANGE	85 ~ 132VAC / 176 ~ 264VAC selected by switch 248 ~ 370VDC
	FREQUENCY RANGE	47 ~ 63Hz
	EFFICIENCY (Typ.)	79.5%
	AC CURRENT	4.2A/115VAC 2.3A/230VAC
	INRUSH CURRENT (max.)	COLD START 30A/115VAC 60A/230VAC
LEAKAGE CURRENT	<2mA / 240VAC	
PROTECTION	OVER LOAD	105 ~ 150% rated output power Protection type Hiccup mode, recovers automatically after fault condition is removed.
	ENVIRONMENT	WORKING TEMP. -10 ~ +60°C (Refer to output load derating curve)
ENVIRONMENT	WORKING HUMIDITY	20 ~ 90% RH non-condensing
	STORAGE TEMP., HUMIDITY	-20 ~ +85°C , 10 ~ 95% RH
	TEMP. COEFFICIENT	±0.03%/°C (0 ~ 50°C)
	VIBRATION	10 ~ 500Hz, 2G 10min./1cycle, period for 60min. each along X, Y, Z axes
SAFETY & EMC	SAFETY STANDARDS	UL1012, UL60950-1, TUV EN60950-1 Approved
	WITHSTAND VOLTAGE	I/P-O/P:1.5KVAC I/P-FG:1.5KVAC O/P-FG:0.5KVAC
	ISOLATION RESISTANCE	I/P-O/P, I/P-FG, O/P-FG:100M Ohms/500VDC
	EMI CONDUCTION & RADIA	Design refer to FCC Part15 J Conduction Class A
	HARMONIC CURRENT	Compliance to EN61000-3-2,-3
EMS IMMUNITY	Compliance to EN61000-4-2,3,4,5; ENV50204, EN55024, Light industry level, criteria A	
OTHERS	DIMENSION	215*115*50mm (L*W*H)
	PACKING	1.07Kg; 12pcs/13.5Kg/0.92CUFT
NOTE	<ol style="list-style-type: none"> 1. All parameters NOT specially mentioned are measured at 230VAC input, rated load and 25°C of ambient temperature 2. Ripple & noise are measured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf & 47uf parallel capacitor 3. Tolerance : includes set up tolerance, line regulation and load regulation 4. The power supply is considered a component which will be installed into a final equipment. The final equipment musbe re-confirmed that it still meet EMC directives 	